



Switching Transistors

NPN Silicon



2N2369
2N2369A*

*Motorola Preferred Device



CASE 22-03, STYLE 1
TO-18 (TO-206AA)

MAXIMUM RATINGS

Rating	Symbol	Value	Unit
Collector–Emitter Voltage	V_{CEO}	15	Vdc
Collector–Emitter Voltage	V_{CES}	40	Vdc
Collector–Base Voltage	V_{CBO}	40	Vdc
Emitter–Base Voltage	V_{EBO}	4.5	Vdc
Collector Current (10 μ s pulse)	$I_C(\text{Peak})$	500	mA
Collector Current — Continuous	I_C	200	mA
Total Device Dissipation @ $T_A = 25^\circ\text{C}$ Derate above 25°C	P_D	0.36 2.06	Watt mW/ $^\circ\text{C}$
Total Device Dissipation @ $T_C = 100^\circ\text{C}$ Derate above 100°C	P_D	0.68 6.85	Watts mW/ $^\circ\text{C}$
Operating and Storage Junction Temperature Range	T_J, T_{stg}	-65 to +200	$^\circ\text{C}$

THERMAL CHARACTERISTICS

Characteristic	Symbol	Max	Unit
Thermal Resistance, Junction to Ambient	$R_{\theta JA}$	486	$^\circ\text{C}/\text{W}$
Thermal Resistance, Junction to Case	$R_{\theta JC}$	147	$^\circ\text{C}/\text{W}$

ELECTRICAL CHARACTERISTICS ($T_A = 25^\circ\text{C}$ unless otherwise noted)

Characteristic	Symbol	Min	Max	Unit
----------------	--------	-----	-----	------

OFF CHARACTERISTICS

Collector–Emitter Breakdown Voltage ($I_C = 10 \mu\text{A}, V_{BE} = 0$)	$V_{(BR)CES}$	40	—	Vdc
Collector–Emitter Sustaining Voltage ⁽¹⁾ ($I_C = 10 \text{ mAdc}, I_B = 0$)	$V_{CEO(sus)}$	15	—	Vdc
Collector–Base Breakdown Voltage ($I_C = 10 \mu\text{A}, I_B = 0$)	$V_{(BR)CBO}$	40	—	Vdc
Emitter–Base Breakdown Voltage ($I_E = 10 \mu\text{Adc}, I_C = 0$)	$V_{(BR)EBO}$	4.5	—	Vdc
Collector Cutoff Current ($V_{CB} = 20 \text{ Vdc}, I_E = 0$) ($V_{CB} = 20 \text{ Vdc}, I_E = 0, T_A = 150^\circ\text{C}$)	I_{CBO}	—	0.4 30	μAdc
Collector Cutoff Current ($V_{CE} = 20 \text{ Vdc}, V_{BE} = 0$)	I_{CES}	—	0.4	μAdc
Base Current ($V_{CE} = 20 \text{ Vdc}, V_{BE} = 0$)	I_B	—	0.4	μAdc

1. Pulse Test: Pulse Width $\leq 300 \mu\text{s}$, Duty Cycle $\leq 2.0\%$.

Preferred devices are Motorola recommended choices for future use and best overall value.

2N2369 2N2369A

ELECTRICAL CHARACTERISTICS ($T_A = 25^\circ\text{C}$ unless otherwise noted) (Continued)

Characteristic	Symbol	Min	Max	Unit
ON CHARACTERISTICS				
DC Current Gain ⁽¹⁾ ($I_C = 10\text{ mA}$, $V_{CE} = 1.0\text{ Vdc}$)	h_{FE}	40	120	—
2N2369		—	120	
2N2369A		—	120	
($I_C = 10\text{ mA}$, $V_{CE} = 1.0\text{ Vdc}$, $T_A = -55^\circ\text{C}$)	2N2369	20	—	
($I_C = 10\text{ mA}$, $V_{CE} = 0.35\text{ Vdc}$, $T_A = -55^\circ\text{C}$)	2N2369A	20	—	
($I_C = 30\text{ mA}$, $V_{CE} = 0.4\text{ Vdc}$)	2N2369A	30	—	
($I_C = 100\text{ mA}$, $V_{CE} = 1.0\text{ Vdc}$)	2N2369A	20	—	
($I_C = 100\text{ mA}$, $V_{CE} = 2.0\text{ Vdc}$)	2N2369	20	—	
Collector–Emitter Saturation Voltage ⁽¹⁾ ($I_C = 10\text{ mA}$, $I_B = 1.0\text{ mA}$)	$V_{CE(sat)}$	—	0.25	Vdc
2N2369		—	0.20	
2N2369A		—	0.20	
($I_C = 10\text{ mA}$, $I_B = 1.0\text{ mA}$, $T_A = +125^\circ\text{C}$)	2N2369A	—	0.30	
($I_C = 30\text{ mA}$, $I_B = 3.0\text{ mA}$)	2N2369A	—	0.25	
($I_C = 100\text{ mA}$, $I_B = 10\text{ mA}$)	2N2369A	—	0.50	
Base–Emitter Saturation Voltage ⁽¹⁾ ($I_C = 10\text{ mA}$, $I_B = 1.0\text{ mA}$)	$V_{BE(sat)}$	0.70	0.85	Vdc
($I_C = 10\text{ mA}$, $I_B = 1.0\text{ mA}$, $T_A = +125^\circ\text{C}$)	All Types	0.59	—	
($I_C = 10\text{ mA}$, $I_B = 1.0\text{ mA}$, $T_A = -55^\circ\text{C}$)	2N2369A	—	1.02	
($I_C = 30\text{ mA}$, $I_B = 3.0\text{ mA}$)	2N2369A	—	1.15	
($I_C = 100\text{ mA}$, $I_B = 10\text{ mA}$)	2N2369A	—	1.60	

SMALL–SIGNAL CHARACTERISTICS

Current–Gain — Bandwidth Product ($I_C = 10\text{ mA}$, $V_{CE} = 10\text{ Vdc}$, $f = 100\text{ MHz}$)	f_T	500	—	MHz
Output Capacitance ($V_{CB} = 5.0\text{ Vdc}$, $I_E = 0$, $f = 1.0\text{ MHz}$)	C_{obo}	—	4.0	pF
Input Capacitance ($V_{EB} = 1.0\text{ Vdc}$, $I_C = 0$, $f = 1.0\text{ MHz}$)	C_{ibo}	—	4.0	pF

SWITCHING CHARACTERISTICS

Storage Time ($I_C = I_{B1} = 10\text{ mA}$, $I_{B2} = -10\text{ mA}$)	t_s	—	13	ns
Turn–On Time ($I_C = 10\text{ mA}$, $I_{B1} = 3.0\text{ mA}$, $I_{B2} = -1.5\text{ mA}$, $V_{CC} = 3.0\text{ Vdc}$)	t_{on}	—	12	ns
Turn–Off Time ($I_C = 10\text{ mA}$, $I_{B1} = 3.0\text{ mA}$, $I_{B2} = -1.5\text{ mA}$, $V_{CC} = 3.0\text{ Vdc}$)	t_{off}	—	18	ns

1. Pulse Test: Pulse Width $\leq 300\ \mu\text{s}$, Duty Cycle $\leq 2.0\%$.

SWITCHING TIME EQUIVALENT TEST CIRCUITS FOR 2N2369, 2N3227




Figure 1. t_{on} Circuit — 10 mA




Figure 3. t_{off} Circuit — 10 mA




Figure 2. t_{on} Circuit — 100 mA




Figure 4. t_{off} Circuit — 100 mA

* Total shunt capacitance of test jig and connectors.




Figure 5. Turn-On and Turn-Off Time Test Circuit




Figure 6. Junction Capacitance Variations




Figure 7. Typical Switching Times




Figure 8. Maximum Charge Data




Figure 9. Q_T Test Circuit




Figure 10. Turn-Off Waveform




Figure 11. Storage Time Equivalent Test Circuit




Figure 12. Maximum Collector Saturation Voltage Characteristics




Figure 13. Minimum Current Gain Characteristics




Figure 14. Saturation Voltage Limits





Figure 15. Typical Temperature Coefficients

PACKAGE DIMENSIONS



Motorola reserves the right to make changes without further notice to any products herein. Motorola makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Motorola assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation consequential or incidental damages. "Typical" parameters which may be provided in Motorola data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. Motorola does not convey any license under its patent rights nor the rights of others. Motorola products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the Motorola product could create a situation where personal injury or death may occur. Should Buyer purchase or use Motorola products for any such unintended or unauthorized application, Buyer shall indemnify and hold Motorola and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that Motorola was negligent regarding the design or manufacture of the part. Motorola and are registered trademarks of Motorola, Inc. Motorola, Inc. is an Equal Opportunity/Affirmative Action Employer.

How to reach us:

USA/EUROPE/Locations Not Listed: Motorola Literature Distribution; P.O. Box 20912; Phoenix, Arizona 85036. 1-800-441-2447 or 602-303-5454

JAPAN: Nippon Motorola Ltd.; Tatsumi-SPD-JLDC, 6F Seibu-Butsuryu-Center, 3-14-2 Tatsumi Koto-Ku, Tokyo 135, Japan. 03-81-3521-8315

MFAX: RMFAX0@email.sps.mot.com – TOUCHTONE 602-244-6609
INTERNET: http://Design-NET.com

ASIA/PACIFIC: Motorola Semiconductors H.K. Ltd.; 8B Tai Ping Industrial Park, 51 Ting Kok Road, Tai Po, N.T., Hong Kong. 852-26629298



This datasheet has been download from:

www.datasheetcatalog.com

Datasheets for electronics components.